Ceiling LED Chandelier

START FROM HERE

- Make sure **POWER** is **COMPLETELY OFF** at the fuse box
- Have your fixture installed by a qualified licensed electrician
- · Prepare everything in a clear area
- · Wear gloves at all times during this installation
- · Read instructions carefully before you start assembly
- Keep this installation sheet for future reference

Technical Support: 1-855-855-8926

Please Note:

- This Kuzco LED fixture comes with pre-wired LED module(s)
- Unless instructed, Do Not touch any part of the LED module(s) as any unnecessary contact with the module could cause permanent damage
- For dimming, an ELV (Electronic Low Voltage) or TRIAC type of dimmer is required
- 120V input

1. Remove fixture from its original package

2. Separate mounting plate (1c) from canopy (2a) by removing canopy screws (2b)

3. Attach mounting plate **(1c)** to electrical junction box **(1a)** using junction box screws provided **(1e)** in hardware package

4. To change fixture height, shorten or lengthen wire by removing screw (2c) from canopy (2a) and wire lock (2d) and push or pull wire to your desired length.

Secure screw (2c) in canopy (2a) and wire lock (2d) to lock wire in place

5. Make proper electrical connections (**black** to **hot** "L", **white** to **neutral** "N", **ground** to "**GND**") with wire nuts (**1b**) provided in hardware package and place driver (**4a**) inside canopy (**2a**)

6. Attach canopy (2a) to mounting plate (1c) with canopy screws (2b)

 Secure diffuser (3b) to fixture body (3a) by threading clockwise



