LED Linear Pendant

LP73536

NSTALLATION SHEET

START FROM HERE


- Make sure power is completely off at the fuse box.
- Have your fixture installed by a qualified licensed electrician
- Prepare everything in a clear area.
- Wear gloves at all times during this installation.
- Read instructions carefully before you start assembly.
- Keep this instruction sheet for future reference.

Technical Support: 1-855-855-8926

Please Note:

- This Kuzco LED fixtures comes with pre-wired LED module(s).
- Unless instructed to do so, please do not touch any part of the LED module(s) as any unnecessary contact with the module could cause permanent damage.
- For dimming, an ELV (Electronic Low Voltage) or TRIAC type of dimmer is required.
- 120V input

- 1. Remove the fixture from its original packaging
- 2. Separate the mounting plate (1c) from the canopy (2a) by removing the canopy screws (2b)
- **3.** Attach the mounting plate (1c) to the electrical junction box (1a) using junction box screws provided (1e) in the hardware package
- Make proper electrical connections (black to hot "L", white to neutral "N", ground to "GND") with wire nuts (1b) provided in hardware package and place driver (4a) in canopy (2a)
- **5.** Attach canopy (2a) to mounting plate (1c) with canopy screws (2b)
- **b.** Mark and install ceiling anchors (3b) with screw (3a), opening on ceiling anchor (3b) facing towards canopy (2a). Ideal distance between ceiling anchors (3b) is 35-7/16"
- Place wire onto pulley (3g), insert into ceiling anchor (3b) and secure with screw (3f)
- **8.** Fine tone wire length if necessary, by push and hold wire gripper (2g) and then adjust wire to desired length
- **9.** Tilt fixture plate (5a) to desired position





LED Linear Pendant

LP73536

INSTALLATION SHEET

START FROM HERE

- Make sure power is completely off at the fuse box.
- Have your fixture installed by a qualified licensed electrician
- Prepare everything in a clear area.
- Wear gloves at all times during this installation.
- · Read instructions carefully before you start assembly.
- Keep this instruction sheet for future reference.

Technical Support: 1-855-855-8926

Please Note:

- This Kuzco LED fixtures comes with pre-wired LED module(s).
- Unless instructed to do so, please do not touch any part of the LED module(s) as any unnecessary contact with the module could cause permanent damage.
- For dimming, an ELV (Electronic Low Voltage) or TRIAC type of dimmer is required.
- 120V inpu

FOR ALTERNATIVE SIDE CANOPY INSTALL

- 1. Disconnect output wires on driver (2f)
- 2. Move wire gripper (2g) to bottom of the canopy, secure with nut (2d), and close holes on side of canopy with plugs (2e)
- **3.** Reconnect driver positive wire to center core of hanging cable, and negative to meshed conductor
- **4.** Attach canopy **(2a)** to mounting plate **(1c)** with canopy screws **(2c)**. Position desired amount of wire by pushing gripper **(2g)** on canopy **(2a)**
- **5.** Pull wire through aircraft barrel (4b) and stopper (4d). Secure barrel mount (4f), followed by aircraft barrel (4b) to mounting surface with anchor (4c) and screw (4a). Adjust wire to desired length and secure with set screw (4e). Insert wire gripper (2g) into aircraft barrel (4b) to close
- **6.** Fine tone wire length if necessary, by push and hold wire gripper (2g) and then adjust wire to desired length
- 7. Tilt fixture plate (5a) to desired position

